MABA-009250-CT0068



1:2 Step Up Flux Coupled Balun Transformer

3 - 300 MHz Rev. V4

Features


- 1:2 Impedance
- Surface Mount
- Available on Tape & Reel
- 260° Reflow Compatible
- · RoHS Compliant and Pb Free


Description

MABA-009250-CT0068 is a RoHS compliant 1:2 RF transformer in a low cost, surface mount package. Typical applications include single to balanced mode conversion and impedance matching.

The MABA-009250-CT0068 is available in a SM-22 surface mount package and is designed to be utilized in both RoHS and standard reflow profiles. Parts are packaged in tape & reel.

Functional Schematic





Pin Configuration

Pin#	Function	Pin#	Function
1	Secondary Dot	4	Primary
2	Centre Tap	5	Primary Dot
3	Secondary		

Electrical Specifications: Freq. = 3 - 300 MHz, $T_A = 25$ °C, $Z_0 = 50 \Omega$, $P_{IN} = 0 \text{ dBm}$

Parameter	Units	Min.	Тур.	Max.
Impedance Ratio	ratio	_	2:1	_
Insertion Loss	dB	_	0.7	1.6
Amplitude Balance	dB	_	0.4	±1.2
Phase Balance	0	_	_	±2.0

Ordering Information¹

Part Number	Description	
MABA-009250-CT0068	Tape & Reel	

1. Reference Application Note M513 for reel size information.

Absolute Maximum Ratings^{2,3}

Parameter	Absolute Maximum	
Input RF Power	250 mW	
DC Current	240 mA	
Operating Temperature	-40°C to +85°C	

- 2. Exceeding any one or combination of these limits may cause permanent damage to this device.
- MACOM does not recommend sustained operation near these survivability limits.

MACOM Technology Solutions Inc. (MACOM) and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice.

Visit www.macom.com for additional data sheets and product information.




1:2 Step Up Flux Coupled Balun Transformer

3 - 300 MHz Rev. V4

Typical Performance Curves⁴



Amplitude Balance 1 0.5 -0.5 -1 3 102 201 300




4. Full temperature plots available on request




1:2 Step Up Flux Coupled Balun Transformer

3 - 300 MHz Rev. V4


Application Schematic




Recommended Footprint



Carrier Tape Orientation



Outline Drawing^{5,6,7,8}



- 5. Dimensions in mm
- 6. Tolerance: ±0.2 mm unless otherwise noted
- 7. Model number and lot code are printed on the reel
- 8. Plating finish: ENIG

Tape & Reel Information

Parameter	Units	Value	
Qty per reel	-	2000	
Reel Size	mm	330	
Tape Width	mm	12.00	
Pitch	mm	8.00	
Ao	mm	4.00	
Во	mm	4.00	
Ko	mm	2.90	
Orientation	-	F5	
Reference Application Note ANI-019 for orientation			

MABA-009250-CT0068



1:2 Step Up Flux Coupled Balun Transformer 3 - 300 MHz

Rev. V4

MACOM Technology Solutions Inc. All rights reserved.

Information in this document is provided in connection with MACOM Technology Solutions Inc ("MACOM") products. These materials are provided by MACOM as a service to its customers and may be used for informational purposes only. Except as provided in MACOM's Terms and Conditions of Sale for such products or in any separate agreement related to this document, MACOM assumes no liability whatsoever. MACOM assumes no responsibility for errors or omissions in these materials. MACOM may make changes to specifications and product descriptions at any time, without notice. MACOM makes no commitment to update the information and shall have no responsibility whatsoever for conflicts or incompatibilities arising from future changes to its specifications and product descriptions. No license, express or implied, by estoppels or otherwise, to any intellectual property rights is granted by this document.

THESE MATERIALS ARE PROVIDED "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, RELATING TO SALE AND/OR USE OF MACOM PRODUCTS INCLUDING LIABILITY OR WARRANTIES RELATING TO FITNESS FOR A PARTICULAR PURPOSE, CONSEQUENTIAL OR INCIDENTAL DAMAGES, MERCHANTABILITY, OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT. MACOM FURTHER DOES NOT WARRANT THE ACCURACY OR COMPLETENESS OF THE INFORMATION, TEXT, GRAPHICS OR OTHER ITEMS CONTAINED WITHIN THESE MATERIALS. MACOM SHALL NOT BE LIABLE FOR ANY SPECIAL, INDIRECT, INCIDENTAL, OR CONSEQUENTIAL DAMAGES, INCLUDING WITHOUT LIMITATION, LOST REVENUES OR LOST PROFITS, WHICH MAY RESULT FROM THE USE OF THESE MATERIALS.

MACOM products are not intended for use in medical, lifesaving or life sustaining applications. MACOM customers using or selling MACOM products for use in such applications do so at their own risk and agree to fully indemnify MACOM for any damages resulting from such improper use or sale.

4