### E-Series RF 1:1 Transformer with Tap 50 - 1200 MHz

### Features


- 1:1 Impedance Ratio
- Surface Mount Package
- Tape and Reel Packaging Available
- RoHS\* Compliant & 260°C Reflow Compatible

#### Description

The MABA-009602-ES2922 is a RoHS compliant 1:1 RF transmission line transformer in a surface mount package (SM-22).

Typical applications include single to balanced mode conversion.

### Schematic



### **Pin Configuration**

Pin #	Function	Pin #	Function
1	Output Thru	4	Input
2	No Connection	5	Ground
3	Output Coupled		

### Electrical Specifications: Freq. = 50 - 1200 MHz, $T_A = 25^{\circ}C$ , $Z_0 = 50 \Omega$ , $P_{IN} = 0 \text{ dBm}$

Parameter	Freq. Test Conditions (MHz)	Units	Min.	Тур.	Max.
Insertion Loss	50 - 600 600 - 1200	dB	_	0.5 1.0	1.0 2.0
Amplitude Balance	50 - 600 600 - 1200	dB	_	0.1 0.5	0.3 1.0
Phase Balance	50 - 600 600 - 1200	o	_	1.0 4.0	3.0 13.0

### **Ordering Information**

Parameter	Package	
MABA-009602-ES2922	2000 piece reel	

### **Absolute Maximum Ratings**

Parameter	Absolute Maximum	
RF Power	250 mW	
DC Current	50 mA	
Operating Temperature	-40°C to +85°C	
Storage Temperature	-55°C to +125°C	

1




Rev. V4

MACOM Technology Solutions Inc. (MACOM) and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice. Visit <u>www.macom.com</u> for additional data sheets and product information.


# E-Series RF 1:1 Transformer with Tap 50 - 1200 MHz

### **Typical Performance Curves**






Insertion Loss Pin 4-3



188 186 184 182 degree 180 178 176 174 172 170 . 250 . 450 . 650 . 850 . 1050 50 Frequency (MHz)

Phase Imbalance





MACOM Technology Solutions Inc. (MACOM) and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice. Visit <u>www.macom.com</u> for additional data sheets and product information.


2



Rev. V4

# E-Series RF 1:1 Transformer with Tap 50 - 1200 MHz


### Case Style SM-22



Dimensions are inches (millimeters)  $\pm 0.015$  (0.38) unless otherwise specified. Drawing not to scale.

### **Tape & Reel Information**

DIRECTION OF FEED



#### Dimensions

Item	Dimension (mm)
Ao	4.10 +/-0.1
Bo	6.50 +/-0.1
Ko	4.00 +/-0.1
W	16.00 +/-0.3
P1	8.00 +/-0.1

MACOM Technology Solutions Inc. (MACOM) and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice. Visit www.macom.com for additional data sheets and product information.



Rev. V4

E-Series RF 1:1 Transformer with Tap 50 - 1200 MHz



Rev. V4

MACOM Technology Solutions Inc. All rights reserved.

Information in this document is provided in connection with MACOM Technology Solutions Inc ("MACOM") products. These materials are provided by MACOM as a service to its customers and may be used for informational purposes only. Except as provided in MACOM's Terms and Conditions of Sale for such products or in any separate agreement related to this document, MACOM assumes no liability whatsoever. MACOM assumes no responsibility for errors or omissions in these materials. MACOM may make changes to specifications and product descriptions at any time, without notice. MACOM makes no commitment to update the information and shall have no responsibility whatsoever for conflicts or incompatibilities arising from future changes to its specifications and product descriptions. No license, express or implied, by estoppels or otherwise, to any intellectual property rights is granted by this document.

THESE MATERIALS ARE PROVIDED "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, RELATING TO SALE AND/OR USE OF MACOM PRODUCTS INCLUDING LIABILITY OR WARRANTIES RELATING TO FITNESS FOR A PARTICULAR PURPOSE, CONSEQUENTIAL OR INCIDENTAL DAMAGES, MERCHANTABILITY, OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT. MACOM FURTHER DOES NOT WARRANT THE ACCURACY OR COMPLETENESS OF THE INFORMATION, TEXT, GRAPHICS OR OTHER ITEMS CONTAINED WITHIN THESE MATERIALS. MACOM SHALL NOT BE LIABLE FOR ANY SPECIAL, INDIRECT, INCIDENTAL, OR CONSEQUENTIAL DAMAGES, INCLUDING WITHOUT LIMITATION, LOST REVENUES OR LOST PROFITS, WHICH MAY RESULT FROM THE USE OF THESE MATERIALS.

MACOM products are not intended for use in medical, lifesaving or life sustaining applications. MACOM customers using or selling MACOM products for use in such applications do so at their own risk and agree to fully indemnify MACOM for any damages resulting from such improper use or sale.

<sup>4</sup> 

MACOM Technology Solutions Inc. (MACOM) and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice. Visit <u>www.macom.com</u> for additional data sheets and product information.