# MABA-009822-715254



## 1:1 Transmission Line Transformer

# 4.5 - 3000 MHz

Rev. V2


### **Features**

- Surface Mount Package
- 1:1 Impedance
- Wide Frequency Range
- · RoHS Compliant, Lead Free
- Available on Tape and Reel


# **Description**

The MABA-009822-715254 is a 1:1 RF transmission line transformer in a surface mount package. The windings are welded to the package substrate for improved reliability and to eliminate Pb content. Ideally suited for high volume cellular and wireless application.

### **Schematic**







# **Pin Configuration**

Pin No.	Function	
1	Secondary Dot	
2	Not Connected	
3	Secondary	
4	Primary	
5	Primary Dot	

# Electrical Specifications: Freq. = 4.5 - 3000 MHz, $T_A$ = 25°C, $Z_0$ = 50 $\Omega$ , $P_{IN}$ = 0 dBm

Parameter	Test Conditions	Units	Min.	Тур.	Max.
	4.5 - 1000			0.32	1.0
Insertion Loss	1000 - 2000	dB	_	_	2.0
	2000 - 3000			_	3.5
Amplitude Unbalance	1	dB	_	0.5	1.0
Phase Unbalance	_	0	_	5	20

# **Ordering Information**

Parameter	Package
MABA-009822-715254	2000 piece reel

# **Absolute Maximum Ratings**

Parameter	Absolute Maximum		
RF Power	250 mW		
DC Current	50 mA		
Operating Temperature	-40°C to +85°C		
Storage Temperature	-55°C to +125°C		

1

# MABA-009822-715254



## 1:1 Transmission Line Transformer

# 4.5 - 3000 MHz Rev. V2

# Typical Performance: $T_A = 25^{\circ}C$ , $Z_0 = 50 \Omega$ , $P_{IN} = 0 dBm$


### Insertion Loss

# INSERTION LOSS (0 to -10 dB) vs FREQ (30 kHz to 3 GHz)


### Amplitude Unbalance



### Phase Unbalance



### Input Impedance






## 1:1 Transmission Line Transformer


4.5 - 3000 MHz Rev. V2

# Case Style SM-22



Dimensions are inches (millimeters)  $\pm 0.015$  (0.38) unless otherwise specified. Drawing not to scale.

# Tape & Reel Information



### **Dimensions**

Item	Dimension (mm)		
Ao	4.00 +/-0.1		
Bo	4.30 +/-0.1		
Ko	2.90 +/-0.1		
W	12.00 +/-0.3		
P1	8.00 +/-0.1		

# MABA-009822-715254



1:1 Transmission Line Transformer

4.5 - 3000 MHz Rev. V2

### MACOM Technology Solutions Inc. All rights reserved.

Information in this document is provided in connection with MACOM Technology Solutions Inc ("MACOM") products. These materials are provided by MACOM as a service to its customers and may be used for informational purposes only. Except as provided in MACOM's Terms and Conditions of Sale for such products or in any separate agreement related to this document, MACOM assumes no liability whatsoever. MACOM assumes no responsibility for errors or omissions in these materials. MACOM may make changes to specifications and product descriptions at any time, without notice. MACOM makes no commitment to update the information and shall have no responsibility whatsoever for conflicts or incompatibilities arising from future changes to its specifications and product descriptions. No license, express or implied, by estoppels or otherwise, to any intellectual property rights is granted by this document.

THESE MATERIALS ARE PROVIDED "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, RELATING TO SALE AND/OR USE OF MACOM PRODUCTS INCLUDING LIABILITY OR WARRANTIES RELATING TO FITNESS FOR A PARTICULAR PURPOSE, CONSEQUENTIAL OR INCIDENTAL DAMAGES, MERCHANTABILITY, OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT. MACOM FURTHER DOES NOT WARRANT THE ACCURACY OR COMPLETENESS OF THE INFORMATION, TEXT, GRAPHICS OR OTHER ITEMS CONTAINED WITHIN THESE MATERIALS. MACOM SHALL NOT BE LIABLE FOR ANY SPECIAL, INDIRECT, INCIDENTAL, OR CONSEQUENTIAL DAMAGES, INCLUDING WITHOUT LIMITATION, LOST REVENUES OR LOST PROFITS, WHICH MAY RESULT FROM THE USE OF THESE MATERIALS.

MACOM products are not intended for use in medical, lifesaving or life sustaining applications. MACOM customers using or selling MACOM products for use in such applications do so at their own risk and agree to fully indemnify MACOM for any damages resulting from such improper use or sale.